

Amber18-bf11 (Volta)

ウェブページ

<http://ambermd.org/>

バージョン

Amber 18-bf11 + AmberTools 18-bf12

ビルド環境

- Intel Compiler 17.0.8
- Intel MKL 2017 update 4
- Intel MPI 2017.0.4
- CUDA 9.1.85
- Python 2.7

ビルドに必要なファイル

- Amber18.tar.bz2
- AmberTools18.tar.bz2
- (Amber18 update.1-11; スクリプト内で取得)
- (AmberTools18 update.1-12; スクリプト内で取得)

ビルド手順

```
#!/bin/sh

VERSION=18
TOOLSVERSION=18

INSTALL_DIR="/local/apl/lx/amber18-bf11v"
TARBALL_DIR="/home/users/${USER}"

PARALLEL=12

#-----
module purge
module load intel_parallelstudio/2017update8
module load cuda/9.1

export AMBERHOME=${INSTALL_DIR}
export CUDA_HOME="/local/apl/lx/cuda-9.1"

export LANG=C
export LC_ALL=C

# install directory has to be prepared before running this script
if [ ! -d $AMBERHOME ]; then
    echo "Create $AMBERHOME before running this script."
    exit 1
fi

# the install directory must be empty
if [ "$(ls -A $AMBERHOME)" ]; then
    echo "Target directory $AMBERHOME not empty"
    exit 2
fi

ulimit -s unlimited

# prep files
cd $AMBERHOME
```

```

bunzip2 -c ${TARBALL_DIR}/Amber${VERSION}.tar.bz2 | tar xf -
bunzip2 -c ${TARBALL_DIR}/AmberTools${TOOLSVERSION}.tar.bz2 | tar xf -

mv amber${VERSION}/* .
rmdir amber${VERSION}

# apply patches if exists
./update_amber --update
# configure python separately (miniconda)
AmberTools/src/configure_python
$AMBERHOME/bin/amber.conda install mkl-rt --yes

echo "[GPU serial edition (three versions)]"
./configure --no-updates -volta -cuda gnu
make -j${PARALLEL} install && make clean

echo "[GPU parallel edition (three versions)]"
./configure --no-updates -volta -mpi -cuda gnu
make -j${PARALLEL} install && make clean
# tests of GPU versions will be done elsewhere

echo "[CPU serial edition]"
LANG=C ./configure --no-updates -mkl intel
make -j${PARALLEL} install
. ${AMBERHOME}/amber.sh
make test.serial
make clean

echo "[CPU openmp edition]"
LANG=C ./configure --no-updates -openmp -mkl intel
make -j${PARALLEL} install
make test.openmp
make clean

echo "[CPU parallel edition]"
LANG=C ./configure --no-updates -intelmpi -mkl intel
make -j${PARALLEL} install
export DO_PARALLEL="mpirun -np 2"
make test.parallel
export DO_PARALLEL="mpirun -np 4"
cd test && make test.parallel.4proc

cd $AMBERHOME
make clean && chmod 700 src

```

注意

- GPUバージョンは Volta 世代の GPU (V100)をターゲットにしています。Pascal 世代の GPU (P100)では動作しませんのでご注意ください。
- module 名は amber/18/bugfix11-volta です。
- ファイルは /local/api/lx/amber18-bf11v 以下にインストールされています。
- サンプルは samples/ 以下にあります。
- 環境設定スクリプト(amber.sh, amber.csh)は /local/api/lx/amber18-bf11v 直下にあります。CUDA-9.1のパス設定はこのスクリプトでは行われないことに注意してください。
- CUDA版のバイナリを使う際には、CUDA-9.1のパスを明示的に指定する必要があります。samples/以下にあるgpu用サンプルを参考にしてください
- テストのログはlogs/以下に置いてあります。cuda以外のテストはフロントエンドノードで行っています。